RS485 Modbus RTU Relay (DIN Rail, 8 channels relay + 8 inputs, 2 counters)



Rating: Not Rated Yet
Price:
Sales price: 1240,00 ???

Ask a question about this product

Manufacturer: ???????

Description

Modbus RTU operated module with 8 relays, 8 opto-isolated inputs and 2 counters (counters for 1-st and 2-nd inputs).

Size: standard DIN-rail 157 mm-wide enclosure (157x110(including connector)x86 mm).

Commands: standard Modbus RTU commands read relay state, change relay state, read input state, read input counters value, change port baudrate, set module address, clear counters.

Indication: 8 relay state LED, 8 input state LED, 1 power on LED.

Maximal output load: 7A 250VAC / 10A 125VAC / 10A 30VDC.

Power supply: 12V 400mA.

Power consumption: stanby - 90 mA, all relays activated - 370 mA.

Inputs: 8 opto-isolated discrete inputs with permanent LED state indication.

Counters: 2 counters of input events.

Memory: non-volatile memory chip for settings and counters.

Connection: screw connectors.

Modbus address: (can be changed by Modbus command) 0 ...255 (default address: 0x01).

Baudrate: (can be changed by Modbus command) 2400, 4800, 9600, 19200, 28800, 38400, 56000, 57600, 115200, 128000, 256000 (default is 9600).

Port settings: 8n1.

Manual and testing software will be sent along with the module.

Reviews

There are yet no reviews for this product.